

## INSTALLATION INSTRUCTION LED DOME LIGHT



### TECHNICAL DATA:

MODEL	WATTS	LUMENS	BEAM ANGLE	BODY TYPE	TOTAL CURRENT	LUMEN PER WATTS	INPUT POWER	SHAPE	DIMENSION (LxWxH)
VT-8618	18W	1800LM	Sphere 360°	PP+PMMA	100mA	100lm/w	AC:220-240, 50/60Hz	ROUND	ø225x60mm
VT-8624	24W	2400LM	Sphere 360°	PP+PMMA	170mA	100lm/w	AC:220-240, 50/60Hz	ROUND	ø295x65mm
VT-8630	30W	3000LM	Sphere 360°	PP+PMMA	140mA	100lm/w	AC:220-240, 50/60Hz	ROUND	ø420x65mm

### SENSOR TECHNICAL DATA:

DIMENSION	INPUT POWER	STANDBY POWER	WORKING FREQUENCY OF RADAR MODULE	INSTALLATION HEIGHT
16mm*16mm*2.2mm	DC: 5V	5V @ <12mA	5.8GHz±75MHz	3m
DETECTION RADIUS	INITIALIZATION TIME	HOLDUP TIME	WORKING TEMPERATURE	AMBIENT LIGHT THRESHOLD
2-4m	4 sec	1 Min	-20°C ~ 85°C	30Lux

'This product contains a light source of energy efficiency class <F>', where <F> shall be replaced by the energy efficiency class of the contained light source.

### INTRODUCTION & WARRANTY


Thank you for selecting and buying V-TAC product. V-TAC will serve you the best. Please read these instructions carefully before starting the installation and keep this manual handy for future reference. If you have any another query, please contact our dealer or local vendor from whom you have purchased the product. They are trained and ready to serve you at the best. The warranty is valid for 2 years from the date of purchase. The warranty does not apply to damage caused by incorrect installation or abnormal wear and tear. The company gives no warranty against damage to any surface due to incorrect removal and installation of the product. The products are suitable for 10-12 Hours Daily operation. Usage of product for 24 Hours a day would void the warranty. This product is warranted for manufacturing defects only.

**WARNING:**  


- Please make sure to turn off the power before starting the installation.
- Installation must be performed by a certified person.
- The light source of this luminaire is not replaceable, when the light source reaches its end of life the whole luminaire should be replaced.
- For Indoor use only
- If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or his service agent or a similar qualified person in order to avoid a hazard.
- Method of attachment of the cable or cord such that any replacement can only be made by the manufacturer, his service agent or similar qualified person.



**MULTI-LANGUAGE  
MANUAL QR CODE**  
Please scan the QR code to access the manual in multiple languages.



This marking indicates that this product should not be disposed of with other household wastes.



Replaceable light source by a professional



Caution, risk of electric shock.



RoHS

