

CorePro LEDtube HF T5 HE - 1500mm


Ballast Compatibility



KEY

	Ballast is compatible
*	Ballast is compatible, light output may differ >10% compared to specifications
**	Ballast is compatible, light output may differ >20% compared to specifications
	Ballast is not compatible

This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions



CorePro LEDtube HF 1500mm
HE 20.5W 8xx T5

Model number / (Short) EOC code:
9290037747 / 872016929552000
9290037748 / 872016929554400
9290037749 / 872016929556800

AC (50Hz) on HF Ballast Compatible

	Ballast type	12nc	Lamps on ballast	
PHILIPS	HF-S 128-35 TL5 II	9137130332	1	
	HF-Pi 1 28/35/49/54 TL5 EII 220-240	9137006241	1	
	HF-Ri TD 1 28/35/49/54 TL5 E+	9137006956	1	
	HF-Ri TD 1 35/49/80 TL5 E+	9137006957	1	
	HF-Ri TD 1 35/49/80 TL5 E+	9137006957	1	
	HF-Pi 1 28/35/49/80 TL5 EII	9137006525	1	
	HF-P 1 14-35 TL5 HE III IDC 4CIC	9137130310	1	*
	HF-P 1 14-35 TL5 HE III IDC C2E	9137130310	1	*
	HF-R Es 114-35 TL5	9137006616	1	
	HF-R 114-35 TL5 EII	9137006198	1	
	HF-P 135 TL5 220-240	9137001367	1	
	HF-P 135 TL5 220-240	9137001726	1	
	HF-Pi 1 28/35/49/80 TL5 EII 220-240	9137006525	1	
	HF-S 114-35 TL5 II	9137130429	1	
	HF-S 1 14-35 TL5 HE II	9137130420	1	
	HF-P 1 14-35 TL5 HE EII 220-240	9137006129	1	**
	HF-Ri TD 1 28-35-49-54 TL5 E+	9137006560	1	
	HF-P 235 TL5 220-240	9137001212	2	
	HF-Pi 2 28/35/49/54 TL5 EII 220-240	9137006243	2	
	HF-Pi 2 28/35/49/80 TL5 EII	9137006526	2	
	HF-Ri TD 2 28/35/49/54 TL5 E+	9137006958	2	
	HF-P 2 14-35 TL5 HE III IDC	9137130311	2	**
	HF-S 2 14-35 TL5 HE II	9137130421	2	**
	HF-R Es 214-35 TL5	9137006617	2	
	HF-Pi 2 14/21/24/39 TL5 EII 220-240	9137006242	2	
	HF-Pi 2 28/35/49/80 TL5 EII 220-240	9137006526	2	
	HF-R 214-35 TL5 EII	9137006195	2	
	HF-Ri TD 2 28/35/49/54 TL5 E+	9137006561	2	
HF-Ri TD 2 14/21/24/39 TL5 E+	9137006709	2		
HF-Ri TD 1 14/21/24/39 TL5 E+	913700608	1		
HF-Ri TD 2 14/21/24/39 TL5 E+	9137006984	2		
HF-Pi 2 14/21/24/39 TL5 EII 220-240	9137006242	2		
OSRAM	QT-FIT5 1x14-35		1	
	QTP5 1x14-35		1	
	QT-FIT5 2x14-35		2	*
	QTP5 2x14-35		2	**
	Qti 1x35/49/80 GII		1	*
	Qti 1x35/49/80		1	
	Qti 1x28/54/35/49 GII		1	**
	Qti 1x35/49/80 DIM		1	
	Qti DALI 1x35/49/80 DIM		1	*
	Qti 2x35/49/80 GII		2	**
	Qti 2x28/54/35/49 GII		2	
	Qti 2x35/49 DIM		2	**
	Qti 2x35/49/80 DIM		2	*
Qti DALI 2x35/49/80 DIM		2		
HELVAR	EL1x14-35ngn5		1	**
	EL2x14-35ngn5		2	**
	EL2x14-35s		2	**
TRIDONIC ATCO	PCA 1x35 T5 BASIC Ip	22185080	1	
	PC 2x35 T5 TOP Ip (28000047)	28000047	2	
	PC 2x35 T5 TOP Ip (87500292)	87500292	2	
	PCA 2x35 T5 BASIC Ip	22185081	2	
	PC 1x14-35 T5 TOP Ip	22185157	1	*
	PC 1x14-35 T5 PRO Ip	22185147	1	
	PC 1/14-21-28-35 T5 PRO Ip	22087725	1	
	PC 1/14-21-28-35 T5 PRO Ip	22176096	1	
	PCA 1x35/49/80 T5 ECO Ip	22185096	1	
	PCA 1x35/49/80 T5 EXCEL one4all Ip	22185105	1	
	PCA 1x35/49/80 T5 EXCEL one4all Ip	22176172	1	
	PCA 2x35/49 T5 EXCEL one4all Ip	22185106	2	
	PCA 2x35/49 T5 ECO Ip	22185097	2	
	PC 2/14-35/49/54 T5 PRO-M Ip	22176186	2	
	PC 1/14-35/49/80 T5 PRO-M Ip	22176184	1	

CorePro LEDtube HF T5 HE - 1500mm

Ballast Compatibility



KEY

	Ballast is compatible
	* Ballast is compatible, light output may differ >10% compared to specifications
	** Ballast is compatible, light output may differ >20% compared to specifications
	Ballast is not compatible

This document is for information purposes and must be treated as recommendation. Signify attempted to provide best results, results are generated in lab controlled environment and may differ from actual application conditions



	Ballast type	12nc	Lamps on ballast
VOSSLOH-SCHWABE	ELXc 235.232	183114	2
	ELXc 135.220	188921	1
	ELXc 135.231	183113	1
	ELXc 135.856	188093	1
	ELXc 235.857	188094	2
	ELXc 235.221	188922	2
	ELXd 235.735	183059	2
	ELXc 154.633	188946	1
	ELXc 180.634	188947	1
	ELXd 180.605	188334	1
	ELXc 254.636	188949	2
	ELXc 280.637	188950	2
	ELXd 249.606	188335	2
	ELXd 280.630	188604	2
	BAG-HUECO	BCS35.1FX-11/220-240	10077579
BCS35.2FX-11/220-240		10077580	2
MLD54.1FR-11/220-240/DALI		10097815	1
MLS80.1/54.2FR-11/220-240		10071609	1
MLS80.1FR-11/220-240		10071608	1
MLD80.1FR-11/220-240/DALI		10097820	1
MLD54.2FR-11/220-240/DALI		10092121	2
MLD80.2FR-11/220-240/DALI		10101905	2
MLS54.2F-01/220-240		166412	2
MLS80.1/54.2FR-11/220-240		10071609	2
MLS39.1-2FR-11/220-240		10092026	1
MLS39.1-2FR-11/220-240		10092026	2
MLS80.1F-01/220-240			1
D35.1-23051E			1
SCS35.1F-01/220-240			1
TCI	MLS80.1F-01/220-240		1
ARLEN EFA	BE - 214-35 - T5		2
	LYZ-1X14WT5-240		1
	LYZ-1X35WT5-240		1
	LYZ-1X35WT5-110C		1
OTHERS	Direct mains		

CorePro LEDtube HF 1500mm HE 20.5W 8xx T5	
Model number / (Short) EOC code: 9290037747 / 872016929552000 9290037748 / 872016929554400 9290037749 / 872016929556800	
AC (50Hz) on HF Ballast Compatible	
	*
	*
	*
	*
	*
	*
	**
	**
	**
	*
	*
	*
	*
	**
	*

General notes for CorePro LEDtube HF T5 HE - 1500mm

General notes: Refer to the product reference number in the header of the columns to use this product-ballast compatibility list.
 Please note that Philips LEDtubes InstantFit T5 are only tested with HF ballast on AC operation. The performance of Philips LEDtubes InstantFit T5 on HF ballasts with DC operation is not tested and is therefore not guaranteed. Philips LEDtubes InstantFit T5 range is designed to work on HF ballasts only. This document is for information purposes only and must be treated as recommendation. Signify will not accept claims for any damage caused by not implementing the recommendations in this document. Signify does not accept any responsibility, warranty or liability when using Philips LEDtubes with ballasts not mentioned in this list, or when using successor models of the tested ballasts.
 Although Signify aims to provide the most accurate information and test results from controlled experiments the results may vary in different applications. This document focuses on the behaviour of above mentioned Philips LEDtube.
 Please also check and follow the instructions of HF ballast manufacturers for installation instructions.

Always check the latest update of the compatibility list on www.philips.com/ledtube